

microphone shock mount, with female 5 Pin XLR centrally mounted on
Finished in matt black.



- XLR-Female type connector
- Soldering-free wiring
- Rubber panel isolates the microphone from the mounting surface and provides effective reduction of mechanical noise and vibration.
- Specially designed for Clockaudio gooseneck halo microphones, as well as other plug-in microphones with 5 pin XLR-Male type outputs.

MOUNTING/CONNECTIONS

1. Connect a 4-core shielded cable to the screw terminal on the bottom of the mounting plate (The terminal numbers are indicated on the circuit board.)
2. For Clockaudio 5 pin halo microphones connect the "Ground" to PIN 1, "halo -" to PIN 2, "Phase -" to PIN3, "halo +" to PIN 4 and "Phase +" to PIN 5
3. Ensure there is a firm connection between the screw terminals and the cable.
4. Position the shock mount plate on the mounting surface and fix it with the supplied screws.
5. Secure the connection cable below the mounting surface and reserve a length to guarantee the best isolation.

