



Product	Length (L)	Shaft Diameter
C 31E-HALO-RF	200mm (7.8")	8mm (0.32")
C 32E-HALO-RF	300mm (11.8")	8mm (0.32")
C 33E-HALO-RF	400mm (15.75")	8mm (0.32")
C 34E-HALO-RF	500mm (19.7")	8mm (0.32")
C 35E-HALO-RF	600mm (23.6")	8.5mm (0.34")
C 36E-HALO-RF	700mm (27.5")	8.5mm (0.34")

Wiring Configuration For 5 Pin XLR Termination

- PIN 1-----Screen
- PIN 2-----LED -
- PIN 3-----Phase -
- PIN 4-----LED +
- PIN 5-----Phase +

Halo Max Voltage = 12V max current = 30mA

ISSUE	DESCRIPTION	APP'D	DATE	TITLE	DRAWN	TRACED	CHECKED	APPROVED	DATE
1	Cardioid Condensor Microphones with halo and RF Friendly			C 3E-Halo-RF Series	C B				16/10/08
					DRAWING No. 577				

